

## VS 380 Sound



### Sagab by Elma Volt Stick Sound

The original and still the best, Volt Stick is an instant tester for safely checking the presence of an AC voltage, without making any disconnections in cables, wall sockets, fuses, circuit breakers, junction boxes, etc. No current flow is needed for correct operation.

The red indicator in the tip will illuminate and emit a sound on detection of AC voltage simply by applying the tip close to any connection point, or moving it along any insulated cable.— Locates breaks in cables, if it indicates only with red light this means it is time for battery replacement.

- Detects blown fuses inside plugs or fuse holders
- Distinguishes between live and neutral wires in both single and three-phase supplies
- Identifies voltage-carrying cables in junction boxes
- Locates defective in-series light bulbs

Voltage range:230-1000V AC

Response Time:Immediate

Batteries:2 x 1,5V AAA (supplied)

Relative Humidity:80% @ 30°C, 50% @ 40°C

Operating Temperature:-20 ~ +50°C

Overvoltage:CAT III 1000V AC

Dimensions / Weight:145(L) x 18(Ø) mm / 35g (incl. batteries)

